

System

CPU	Intel PXA270 520MHz
Memory	Flash RAM: 320MB
OS	Windows CE 5.0 Professional Plus

Display

240x320 QVGA, Color Transflective TFT, with Touch Screen & backlight

Keypad

18-key, including numeric key, alpha key and function key

Input Device

HF RFID Reader, Keypad, Touch Screen, and Full Alphanumeric Software, 2D Bar Code Scanner

RFID Reader

Frequency: 13.56MHz
Tag Support: ISO15693, ISO14443A, ISO14443B

Indicator

LED

Communication

USB Host & Client
802.11b/g
Bluetooth
Bluetooth supports Bluetooth Printer, Bluetooth Modem, Bluetooth ActiveSync

Audio

MIC
Speaker
Headset Connector
Receiver

Expansion Slot

SDIO Slot

Power Source

Main Battery	3.7V 2200mAh Li-ion battery
Backup Battery	Rechargeable Ni-MH backup battery

Environmental

Operating temperature	-10 °C to 50 °C
Storage temperature	-20 °C to 60 °C
Relative Humidity	5% ~ 95%(non-condensing)
Drop test to Concrete	4 feet
Environmental Sealing	IP64 Anti-microbial casting/protection (PA600L)
Weight	315g with battery
Dimesion	L149.5 X H35.5 X W85mm

Software

Unitech Software Development Kit
Oracle Database Lite
Wave link Avalanche
Microsoft BizTalk Server 2006 R2

Accessories

4 Slot Multi-Bay	Battery Charger
Desktop Cradle	Extended Battery (To be available in Q4 2008)
Holster	Vehicle Quick Charging Cable
Vehicle Dock	

Regulatory Approvals

CE, FCC, BSMI, VCCI, CCC, RoHS compliant



Unitech America

Los Angeles, Houston, Guadalajara
<http://www.ute.com> e-mail: inquiry@ute.com
<http://latin.unitech-adc.com> e-mail: info@latin.ute.com

Unitech Asia Pacific & Middle East

Taipei
<http://www.unitech-utp.com.tw> e-mail: aidcsales@tw.ute.com

Unitech Japan

Tokyo
<http://www.unitech-japan.co.jp> e-mail: sales@jp.ute.com

Unitech Europe

Tilburg / Netherlands
<http://www.unitech-europe.com> e-mail: sales@eu.ute.com

Unitech Greater China

Beijing, Shanghai, Guang Zhou, Xiamen
<http://www.ute.com.cn> unitech@cn.ute.com
Taipei <http://adc-utt.unitech.com.tw> barcode@tw.ute.com

Head Office

Taipei
<http://www.unitech-adc.com> e-mail: marketing@tw.ute.com
RFID team e-mail: rfid@tw.ute.com